

MINI TIMER MT10E



Versatile switch clock for manual or automatic remote control of Marmitek X-10 Modules. Ideal for simulating a presence in your house: it looks like you are always at home. Four different modules can be switched up to 4 times a day. Built-in alarm clock.

APPLICATION

The MT10E Mini Timer can be used to turn Marmitek X-10 Modules on or off at a pre-programmed time. Up to 4 modules can be pre-programmed with 2 'On' times and 2 'Off' times.

The buttons can be used to manually control 8 modules. These modules can be controlled using the Marmitek X-10 Commands 'On', 'Off' and 'Dim'. The MT10 also has buttons for 'All Lights On' and 'All Units Off'.

The mini timer has a 'Security' button, which randomly adjusts the pre-programmed times for the modules every day (up to 1 hour difference). If the lighting in the house is controlled using this method, the house always looks lived-in. The modules are controlled via the mains. No extra wiring required.

The mini timer also has an adjustable alarm clock, which can switch on a module. This means the lights can be switched on when the alarm goes off.

The 'Sleep' function turns the modules on or off at a specific time. This time can be adjusted in increments of 15 minutes.

The mini timer is powered via the mains. A back-up battery will retain the time and settings in case of a power failure.

MINI TIMER MT10E



| | |
|--------------------------|----------------------|
| Power: | 230V +10% -15%, 50Hz |
| Back-up battery: | 9V PP9 |
| Minimal Back-Up Power: | 6V DC |
| Battery empty indicator: | 7.5V +/-0.5V DC |
| Dimensions: | 55x150x110mm |
| Weight: | 590g |
| Colour: | White |

